



ALL AMERICAN MONITORING

Programming Steps – DSC 832/5010

Enable Alarms/Communication Reports:

KEYPAD DISPLAY	ENTER ON KEYPAD	COMMENTS
Enter Section	361	To program phone 1 call direction
Toggle Option 1-----	1 #	1 for Alarms & Restorals.
Enter Section	380	First Communicator Options
Toggle Option 1-----	1 #	Communications Enabled
Enter Section -----	381	Second Communicator Options Make sure 3 is OFF

Enable Open/Close Reports:

KEYPAD DISPLAY	ENTER ON KEYPAD	COMMENTS
Enter Section	365	Open/Close Communicator Cell directions.
Toggle Option 1-----	1 #	Toggle 1 to ON to enable Open/Close reports

Set Communicator Format to SIA:

KEYPAD DISPLAY	ENTER ON KEYPAD	COMMENTS
Enter Section	360	Program alarm Format
Enter Data	04,04	04 is for SIA format

Communicator Programming:

KEYPAD DISPLAY	ENTER ON KEYPAD	COMMENTS
Enter Section	301	Enter Receiver Number OR
Enter Data	*****	Any 10 digits will work
Enter Section	310	Enter Account Number
Enter Data	???	4 Digit Account Number



ALL AMERICAN MONITORING

Wiring the MN02-LTE Cellular Communicator
and Programming the Panel

DSC 832 / 5010

