



ALL AMERICAN MONITORING

Programming Steps – DSC Impassa

Program Keyswitch zone& Output:

| KEYPAD DISPLAY | ENTER ON KEYPAD | COMMENTS |
|-------------------------|-----------------|--|
| Enter Section | 009 | Zone 1 keyswitch |
| Enter Data XX | 00 | Enter 00 for I/O 1 XX is previous value |
| Enter Data XX | 05 | 05 to program Armed Status for I/O 2, XX is previous value |
| Enter Section | 003 | Zone 33 Keyswitch |
| Enter Data XX | 22 # | 22 is for the Zone Type Keyswitch, XX is the previous value, # to go back to Enter Section. |
| Enter Section | 013 | First System Options (to select I/O as Input or PGM) |
| Toggle Option 1----- | 1 | Assuming the panel is defaulted press the toggle buttons until 1 is ON and 2 is OFF |
| | # | # to return to Enter Section |
| Enter Section | 206 | Enter Zone Assignment. |
| Toggle Option 1----- | 1 | Toggle option 1 to ON to enable the Keyswitch zone. |
| | # | Press # to go to the next section |

Enable Open/Close Reports:

| KEYPAD DISPLAY | ENTER ON KEYPAD | COMMENTS |
|-------------------------|-----------------|---|
| Enter Section | 351 | To program phone 1 call direction |
| Toggle Option 1----- | 1 # | Toggle 1 to ON for alarms |
| Enter Section | 367 | Open/Close Communicator Cell directions. |
| Toggle Option 1----- | 1 # | Toggle 1 to ON to enable Open/Close reports |
| Enter Section | 380 | First Communicator Options |
| Toggle Option 1----- | 1 # | Toggle 1 to ON to Communications Enabled |

Set to Contact ID

| KEYPAD DISPLAY | ENTER ON KEYPAD | COMMENTS |
|------------------|-----------------|--|
| Enter Section | 350 | Program alarm Format |
| Enter Data XX | 03 # | 03 is for CID format, XX is the previous programmed value, # to return to Enter Section. |

Program Phone & Account #:

| KEYPAD DISPLAY | ENTER ON KEYPAD | COMMENTS |
|----------------|-----------------|--------------------------|
| Enter Section | 301 | Enter Recevier Number OR |
| Enter Data | ***** | Any 10 Digits Will Work |
| Enter Section | 310 | Enter Account Number |
| Enter Data | ??? | 4 Digit Account Number |
| | # | To get back to main menu |



ALL AMERICAN MONITORING

Wiring the MN02-LTE Cellular Communicator
and Programming the Panel

DSC Impassa

